


Code		Din	nensio	Weight	Resin			
	ø	ØA	В	R	ØE	у	(g)	Weight* (g)
EZS 1	1/2"	34	74	66	63	1.5	230	140
EZS 2	3/4"	34	74	66	63	1.5	220	140
EZS 3	1"	42	74	71	63	2	240	140
EZS 4	1.1/4"	60	98	78	90	2	530	390
EZS 5	1.1/2"	60	98	78	90	2.5	495	390
EZS 6	2"	70	130	88	90	2.5	640	570
EZS 7	2.1/2"	103	142	108	112	3	1400	1400
EZS 8	3"	103	142	108	112	3	1700	1400
* Approxim	ate weig	ht of C	RV 420	resin re	quired	to seal.		

<u>IMPORTANT</u>: instructions for sealing the joints on the following page.



Code		Dime	nsions (	Weight	Resin					
	ø	ØA	В	R	у	(g)	Weight* (g)			
EYS 1	1/2"	32	77	44	1.5	100	35			
EYS 2	3/4"	34	87	51	1.5	150	50			
EYS 3	1"	44	105	62	2	240	100			
* Approximate weight of CRV 420 resin required to seal.										
IMPORTANT: instructions for sealing the joints on the following page.										

# **SEALING JOINTS**



The size and the maximum number of conductors in the In any case, the maximum number of conductors referred following tables refer to the type N07V-K with PVC insulation quality R2. The conductors type N07V-K comply with the national standards CEI 20-35 (CENELEC HD 405-1), CEI 20-22 CEI 20-37 II and I.

(gommaprene, neoprene, etc..) providing they conform to sealing joint under consideration. CENELEC for nominal characteristics and mode of use.

to the same section for the same diameter will be determined by observing the dimension "y" in the tables in the preceding page.

The same sealing joint can be used with wires of different As alternative, the conductors may have different isolation section as long it is respected the "y" dimension of the

Electrical Conductors in Sealing Joints Series EZS															
Ext. Max. Ø	3.5	4.2	4.8	6.3	7.6	8.8	11	12.5	14.5	17	19	21	23.5	26	29.5
Section mm <sup>2</sup>	1.5	2.5	4	6	10	16	25	35	50	70	95	120	150	185	240
JOINTS	Max number of Conductors														
EZS 1	4	3	2	1	1	1	1								
EZS 2	8	5	4	3	1	1	1	1	1						
EZS 3	10	8	8	4	3	2	1	1	1	1					
EZS 4	16	13	11	8	7	4	3	1	1	1	1				
EZS 5	18	16	15	8	8	6	4	4	2	1	1	1	1		
EZS 6	30	20	20	15	10	9	8	7	3	3	2	1	1	1	
EZS 7	40	35	28	21	18	19	12	8	6	4	4	3	2		
EZS 8	50	42	35	30	25	20	12	10	8	7	5	4	3	2	

## Instructions for making the sealing of the joints series EZS ...

### 1. Remove the cap.

resin does not enter in conduits or equipment. The stuffing box can be arranged by cramming the specific fiber type FCE in the interstices between the conductors and the sealing joint and/or between conductor and conductor observing the dimension "y".

The stuffing box is only necessary for the lower entry when the coupling is in a vertical position; in both entries when it is in a horizontal position.

- 3. Retighten the cover place vertically the entry.
- 2. Prepare with the utmost care a "stuffing box" so that the 4. Prepare the resin CRV 420 in sufficient quantity to seal the joint and/or to ensure a duration of 30 minutes.
  - 5. Pour the resin to almost touch on the thread.
  - 6. Screw the cap and tighten.
  - 7. After having poured the resin do not move or stress the conductors for at least 24 hours for joints up to 1" and for at least 48 hours for greater sizes.

Electrical Conductors in sealing joints series EYS															
Ext. Max Ø	3.5 4.2 4.8 6.3 7.6 8.8 11 12.5 14.5 17 19 21 23.5 26 29.5											29.5			
Section mm <sup>2</sup>	1.5	2.5	4	6	10	16	25	35	50	70	95	120	150	185	240
Joints	Max number of Conductors														
EYS 1	4	3	2	1	1	1	1								
EYS 2	7	5	4	3	1	1	1	1	1						
EYS 3	8	7	6	4	3	2	1	1	1	1					

### Instructions for making the sealing of the joints series EYS...

#### 1. Remove the cap.

- 2. Prepare with the utmost care a "stuffing box" so that the resin does not enter in conduits or equipment. The stuffing box can be arranged by cramming the specific fiber type FCE in the interstices between the conductors and the sealing joint and/or between conductor and conductor observing the dimension "y".
- 3. Prepare the resin CRV 420 in sufficient quantity to seal the joint and/or to ensure a duration of 30 minutes.
- 4. Pour the resin to cover the conduttor for a minimum height of D (see table).
- 5. Retighten the cover.
- 6. After having poured the resin do not move or stress the conductors for at least 24 hours.

H20